

## FS1521W2-T SMART RF RADIO MODULE

### Battery type


10 year sealed for life lithium



- For use with Smart RF Ready devices
- When a Smart RF Radio Module (FS1521W2) is fitted within Smart RF ready devices, you can wirelessly interlink up to 50 FireAngel Smart RF products, including FireAngel Connect Gateway
- Radio module frequency band 868.3 MHz
- Transceiver in every module allows sending and receiving data within the network
- Smart RF - when one alarm sounds, they all sound
- Wirelessly interlink up to 50 Smart RF devices on a single network
- 5 years warranty
- Quick, easy, and simple installation

## Technical Specification

Product Dimensions	29x55x30 mm
Supply voltage	3V DC
Battery	3V sealed for life lithium battery
Technology	Smart RF
Master pack quantity	10, 100, 500
Warranty	5 years
Product in pack dimensions	137 (H) x 79 (W) x 30 (D)
Weight	24g
Product in pack weight	31g
Independently tested to	ETSI EN 300 220-2 V2.4.1, ETSI EN 301 489-1 V1.9.2, ETSI EN 301 489-3 V1.6.1
Maximum number of connected units	50 Smart RF devices
Operating Frequency	868 MHz
Range	35m (over 200m in clear air)



### Create a Safety Network

Add a Smart RF Radio Module to wirelessly interlink up to 50 Smart RF devices with a simple 2 step process.



Smoke Alarm



Heat Alarm



CO Alarm



Wireless Alarm Control Unit



Assisted Living Solutions

For further information or sales enquiries, contact your local Specification Manager:  
[www.fireangel.co.uk/specification-manager](http://www.fireangel.co.uk/specification-manager)